



H2001-09/H2001/H2000VRI/ H2000 Single-Line Phones

This telephone user guide details installation, programming, and operation instructions for Scitec healthcare telephones. Please refer to the Scitec website News section and click on Product Notes for updates to this and other Scitec products.

Package Contents

H2001-09/H2001

- Telephone
- Straight line cord
- Clip (for attaching telephone to a bed rail)

H2000VRI/H2000

- Telephone base unit
- Telephone handset unit
- Coiled handset cord
- Straight line cord

Installation

Each healthcare telephone is designed for use behind a registered PBX system. The telephone user or system installer must supply an RJ-11 modular wall jack to connect this telephone to the PBX system. The PBX "station port"

type must be "Industry Standard Analog" or "POTS." This telephone cannot be used with "digital" PBX station ports. Insert one end of the coiled handset cord into the jack on the BOTTOM END of the base unit. Insert the other end of the cord into the jack on the BOTTOM END of the handset. The handset of the unit should now be placed into the base of the unit. Connect the straight line cord from the wall jack to one of the line jack located underneath the base unit. Lift the handset. A dial tone should be heard in the receiver.

Attaching the handset (H2000VRI/H2000)

Connect the supplied coiled handset cord between the jack on the end of handset and the jack marked with a "handset" symbol on the left side of the telephone base unit. Place the handset on the telephone base unit or if wall-mounted, hang it on the desk/wall-mount clip to depress the hook switch.

Wall-mounting (H2000VRI/H2000)

- The wall/desk handset clip located on the front of the phone. In its wall-mount position, the clip extends up to hold the handset in place. Gently pull it up and turn ½ turn to change from desk to wall mount. This clip is spring-loaded and not removable, so that it cannot be lost.
- Turn the telephone over so the telephone face is down.
- Connect line cord to the jack on rear of phone.
- Hold telephone in front of the 2 mushroom shaped mounting posts on the wall jack plate. Line up keyholes on wall-mounting bracket with posts. After engaging wall-mounting bracket with posts, slide telephone down slightly. When properly installed, the telephone will be firmly attached to the wall.

H2000VRI/H2000 Operation

RINGER VOLUME - Adjusts ringer volume to LOW or HI. Located on the left side of the phone near the dataport.

HEARING AID-COMPATIBLE HANDSET - ADA/HAC-compatible

HANDSET JACK - Modular jack to connect coiled handset cord from handset to base unit.

DATA PORT - Provides access to the telephone line for optional connection of modem, fax, or answering machine. Located on the left side of the phone near the ringer control.

DIALING KEYS - 0 - 9 dialing keys.

VOLUME SWITCH - Volume control switch on the handset steps through the three available handset volume levels [Normal - Medium - High].

VISUAL RINGING INDICATOR - Indicates phone is ringing or a message is waiting. Responds to NEON/90V message waiting light format. (H2001-VRI model only)

To Place A Call

Lift the handset, then dial the number desired.

To Answer A Call

Lift the handset.

Adjusting Handset Volume

Press the [VOL] key. Each press of [VOL] moves to the next of three possible settings of [Low - Medium -High], and repeats back to Low volume on the forth press. Adjust as desired.

Adjusting Ringer Volume

The ringer volume control switch is located on the left side of the telephone. There are two ringer volume settings, high and low. Adjust as desired.

H2001-09/H2001 Operation

Placing A Call

Press the [PUSH FOR ON-OFF] key, then dial number as desired.

Taking A Call

Press the [PUSH FOR ON-OFF] key.

Adjusting Phone Volume

Press the [VOL] key, each press steps through the volume settings of [Low - Medium - High - Low]. Adjust as desired.

Ringer Volume Control

Slide the [Off-Low-Hi] volume switch to adjust ringer volume. In all ringer modes, ringing will be accompanied by a flashing light on the telephone.

Flash Key

Enters a 600ms hook switch flash for accessing special telephone system features.

Lighted Keypad

0-9, *, and # dialing keys are illuminated for low light conditions.

Required FCC Notice

This equipment complies with Part 68 of the FCC rules and the requirements adopted by the ACTA. On the bottom of this equipment is a label that contains, among other information, a product identifier in the format US:AAAEQ##TXXXX. If requested, this number must be provided to the telephone company. The REN is used to determine the number of devices that may be connected to a telephone line. Excessive RENs on a telephone line may result in the devices not ringing in response to an incoming call. In most but not all areas, the sum of RENs should not exceed five (5.0). To be certain of the number of devices that may be connected to a line, as determined by the total RENs, contact the local telephone company. The REN for this telephone is part of the product identifier that has the format US:AAAEQ##TXXXX. The digits represented by ## are the REN without a decimal point (e.g., 03 is a REN of 0.3). If this equipment causes harm to the telephone network, the telephone company will notify you in advance that temporary discontinuance of service may be required. If advance notice isn't practical, the Telephone Company will notify you as soon as possible. Also, you will be advised of your right to file a complaint with the FCC if you believe it is necessary. The Telephone Company may make changes in its facilities, equipment, operations, or procedures that could affect the operation of this telephone. If this happens, the Telephone Company will provide advance notice in order for you to make the necessary modifications in order to maintain uninterrupted service. If you experience trouble with this telephone, please contact Scitec, Inc. at (217) 384-6041 for repair or warranty information. If the trouble is causing harm to the telephone network, the Telephone Company may request that you

Required FCC Notice

remove this equipment from the network until the problem is resolved. The customer can do the following repairs: replacement of cords or handset; replacement of window for telephone number. Connection to party line service is subject to state tariffs. Contact the state public utility commission, public service commission or corporation commission for information. This telephone cannot be used on Telephone Company provided coin service. If your home has specially wired alarm equipment connected to the telephone line, ensure the installation of the telephone does not disable your alarm equipment. If you have questions about what will disable alarm equipment, consult your telephone company or a qualified installer. This equipment is hearing aid compatible. If the telephone is used with a leased system, permission of the owner of the equipment must be obtained for connection of the telephone because modification of the host system is often required.

Jacks

A plug and jack used to connect this equipment to the premises wiring and telephone network must comply with the applicable FCC Part 68 rules and requirements adopted by the ACTA. A compliant telephone cord and modular plug is provided with this product. It is designed to be connected to a compatible modular jack that is also compliant.



5025 Galley Road
Colorado Springs, CO 81915 USA
+1.719.638.8821 tel
+1.719.638.8815 fax
info@scitecinc.com
www.scitecinc.com

© 2009 Scitec, Inc.
Scitec is a registered trademark of Scitec Inc.
Specifications subject to change without notice.
Refer to www.scitecinc.com for latest data.
Scitec, Inc. is a minority-owned business.